

Social Alarm S35 Pendant Transmitter



- Easy to use and compact
- Alarm triggering in 2 ways: button or cord
- IP64 waterproof
- Battery life-time of 3 years
- Automatic radio daily message

Its compact size, waterproof case and ease of operation make the S35 Pendant Transmitter the perfect solution for use at home with a Carephone. The alarm is triggered by pulling the cord or pressing the red button, releasing a call to the Carephone.

The S35 Pendant Transmitter can be worn clipped on clothing or around the neck with the pull-cord.

Functions

The S35 Pendant Transmitter is a radio transmitter designed to ensure a secure and easy transmission of an alarm anywhere and at any time. This can be done either by pressing the button or pulling the cord of the S35 Pendant Transmitter. A call for help is then activated and the LED indicator of the transmitter will blink once. In the meantime, the button and the LED indicator of the Carephone receiver will start blinking. An alarm/event data is displayed on the unit and is stored in the buffer of the device.

Cancelling an alarm can be done on the Carephone or remotely by the Social alarm center.

The S35 Pendant Transmitter offers an IP64 waterproof protection and has a built-in automatic battery monitoring with battery low transmission. To ensure correct functioning, it will send an automatic radio daily message to the receiver through radio monitoring.

Certifications and Approvals

CE
R&TTE 1999/5/EC
LVD 73/23/EEC
EMC 89/336/EEC
EN 50130-4
EN 300220-1
EN 60950-1
EN 55022

Parts Included

| Quantity | Component |
|----------|-------------------------|
| 1 | S35 Pendant Transmitter |

Technical Specifications

| | |
|-----------------------------|---|
| Dimensions (H x W x D) | 75 x 40 x 25 mm |
| Weight | 40 g |
| Frequency | 869.2125 MHz |
| Protection class | IP 64 |
| Power supply | 3V lithium battery CR2032 |
| Consumption | <ul style="list-style-type: none"> • Transmission: < 25 mA • Idle mode: < 2 μA |
| Battery life | 3 years, under the following conditions: 3 alarms transmissions without repetition per day and 1 daily test transmission (incl. battery status) |
| Battery alarm | at approx. 20 % remaining |
| Automatic battery test | daily check and at every alarm |
| Permissible temperature | 0 °C to 55 °C |
| Stability (0 to +55 °C) | < \pm 2.5 kHz |
| Modulation | FSK |
| Antenna | Integrated |
| Radiated power | 2 mW |
| Transmission time | 3 x 700 ms |
| Pause between transmissions | 800 ms |
| Minimum range in free field | 250 m |

TeleAlarm SA
 Rue du Pont 23
 2300 La Chaux-de-Fonds
 Switzerland
 info@telealarm.com
www.telealarm.com

TeleAlarm Europe GmbH
 Hertzstraße 2
 04329 Leipzig
 Germany
 info-uk@telealarm.com
www.telealarm.com